



2 x AAA Open Battery Holder with JST PH Connector

PRODUCT ID: 4192

This battery holder connects 2 AAA batteries together in series for powering all kinds of projects. We spec'd these out because the box is open and nicely slim, and 2 AAA's add up to about 3V for low-voltage electronics projects.

Fits any standard AAA battery. When using rechargeable NiMH the output voltage will range from about 2.7V with charged batteries to 1.8V at the end of life with a nominal voltage of 2.4V. When using alkalines, the output will range from 3.2V with new batteries to 2.2V at the end of life with a nominal voltage of about 3V.

The polarity matches that of our [2-pin JST cable](#) and [Li-Ion/Poly batteries](#). Uses a genuine JST connector so it won't 'catch and tear' in JST connector

TECHNICAL DETAILS

- Cable Length: approx 6" long, terminated with a genuine JST-PH 2 pin connector
- Battery holder dimensions (excluding cable): 53 x 24 x 13.3mm