



Item description

Function:

"Building Automation and Control Networks" (BACnet) is a data transfer protocol for building automation that simplifies communication between products from different manufacturers.

The WAGO Touch Panel can be operated as a BACnet building controller and supports the B-BC device profile with all major BACnet objects and interoperability building blocks (BIBBs). The device communicates via BACnet/IP and offers the functionality of a BACnet Client and BACnet Server.

To use BACnet/IP, it is necessary to equip the device with a license.

The BACnet network is configured using the WAGO BACnet Configurator and the *e!COCKPIT* Engineering Software.

Benefits:

- Use the device as a BACnet Building Controller (B-BC)
- Control and detect distributed I/O signals from
- WAGO BACnet/IP Couplers via BACnet Fieldbus Protocol
- Data exchange with other BACnet Devices as a BACnet Client or Server

Use:

Enter the license into *e!COCKPIT*, assign it to a device and load both the license and project into the controller. No other installation steps are required.

Technical Data:

See "Protocol Implementation Conformance Statement" (PICS)

Compatible Touch Panels:

762-43xx/8000-002; Touch Panel 600 Standard Line; PIO 3 hardware configuration

762-53xx/8000-002; Touch Panel 600 Advanced Line; PIO 3 hardware configuration

Subject to changes. Please also observe the further product documentation!



762-63xx/8000-002; Touch Panel 600 Marine Line; PIO 3 hardware configuration

xx is a wildcard; the license applies to all Touch Panel sizes.

Data

Notes

Note	up to 256 BACnet objects
------	--------------------------

System requirements

Other required software	<i>e!COCKPIT</i> version: V1.6.1
-------------------------	----------------------------------

Software data

Supported devices	762-43xx/8000-002: Touch Panel 600 Standard Line; PIO 3 hardware configuration 762-53xx/8000-002: Touch Panel 600 Advanced Line; PIO 3 hardware configuration 762-63xx/8000-002: Touch Panel 600 Marine Line; PIO 3 hardware configuration xx is a wildcard; the license applies to all Touch Panel sizes.
Supported fieldbuses	BACnet/IP; up to 256 BACnet objects

Delivery

Delivery type	License certificate via email (<i>e!COCKPIT</i> already contains the software itself)
License type (note)	Single license allows installation on one device. One license per device is required.
License type (note) (2)	A PC with both Internet connection and <i>e!COCKPIT</i> may be required for license activation.
Licence Generation	DRM

Commercial data

ETIM 8.0	EC001435
ETIM 7.0	EC001435
PU (SPU)	1 pcs
Country of origin	QU
GTIN	4055143947268
Customs tariff number	88888888888

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Environmental Product Compliance

RoHS Compliance Status

Compliant, No Exemption

Downloads

Documentation

Bid Text

2759-2286/211-1000 X81 - Datei	xml 6.1 kB	Download
-----------------------------------	---------------	----------

2759-2286/211-1000 docx - Datei	txt	Download
------------------------------------	-----	----------

ausschreiben.de 2759-2286/211-1000	URL	Download
------------------------------------	-----	----------

System Description

Software – General Product Information	pdf 377.6 kB	Download
--	-----------------	----------

Compatibility Information

Protocol Implementation Conformance Statement for e!RUNTIME BACnet/IP 300 (M)	V 2.1.0 2022 Jun 13	pdf 3.1 MB	Download
--	------------------------	---------------	----------

BACnet Protocol Implementation Conformance Statement (PICS) for e!RUNTIME BACnet/IP 600 (M)	V 2.2.0 2022 May 25	pdf 3.1 MB	Download
--	------------------------	---------------	----------

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 2759-2286/211-1000 Runtime; BACnet; 600; M; Single License; Online activation	URL	Download
---	-----	----------

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.