

## 75 Watt - LP75W Series

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING



DIMMING  
LP75W Series  
75W

### Model: LP75W Series

- Drive Mode: Constant Current or Constant Voltage
- Technology: PFC Corrected 2-Stage Switch Mode
- Output Power: 75W Max.
- Input Voltage: 90 to 305VAC, 47- 63Hz
- Number of Outputs: One
- Output Voltages: 4VDC - 214VDC
- Output Currents: 350mA - 6250mA
- Optional 0-10V or PWM Positive Dimming 10% ~ 100%

### Environmental

1. Operating temperature: Tc 90C Maximum. Reference -30 to +65°C ambient
2. For UL Type TL (Tref Max/Meas. Tref): UL Class 2 86/63°C, UL Non Class 2 90/81°C
3. Storage temperature range: -40 to +85°C
4. Humidity (non-condensing): 5% - 95%RH
5. Cooling: Convection
6. Vibration Frequency: 5-55Hz/2g, 30 minutes
7. Impact resistance: 1g/s
8. MTBF@ 40°C: 474,000 hours @ Full Load per MIL-217F Notice 2.

### Safety and Compliance

1. Class P: UL8750, EN61347, CSA 22.2 safety listed, UL Class P -or- Type TL: UL8750, EN61347, CSA 22.2, UL TL recognized
2. FCC, 47CFR Part 15 Class B certified
3. Water resistant and Dust Proof Design: IP66, NEMA6, for Dry, Damp, Wet Locations.
4. Compact Miniature, Lightweight Design.
5. Safety Isolation between Primary and Secondary
6. Meets EN61000-3-2 & EN61000-3-3 Class C
7. Protection: output over-voltage, output over-current, output short circuit, auto-recovery.
8. EN61000-4-5: 2kV/4kV 8/20 µsec surge protection.

### Electrical Specifications at 25°C

- Input voltage range: 90 to 305VAC
- Frequency: 47- 63Hz
- Power Factor:  $\geq 0.90$  at  $\geq 75\%$  Load, 120Vac/230Vac/277Vac 50/60Hz
- THD%:  $\leq 20\%$  at  $\geq 60\%$  Load, 120Vac/230Vac/277Vac 50/60Hz
- Inrush current:  $<77A$  at 25C, 277V, cold start, Max. Load
- Input current: 1.0A Maximum
- Efficiency: 86% typical at 230Vac Full Load
- Line regulation accuracy:  $\pm 3\%$
- Load regulation accuracy:  $\pm 4\%$
- Leakage current: 277Vac, 700uA typical; Hold up time: half cycle

### Mechanical Dimensions: Inches [mm]

Material: Black Aluminum Housing  
Fully Encapsulated  
Weight: 19 oz ( 538 grams) Typical

### Labeling Example


0-10V CCR Dimmable LED Optimized Driver  
EPtronics, Inc.  
www.EPtronics.com  
800.643.0688 / 010.635.0700

Part Number: LP75W-36-C2100-PRD  
Input Voltage: 90-305VAC 50/60Hz  
Input Current: 1.0 Amp Max  
Output Voltage: 12-36 VDC  
Output Current: 2100 mA CC  
0-10V CCR Dimmable Output  
UL/cUL Class 2 Output  
UL Class P, For Connections use wire rated  $\geq 90C$  (194F)

IP66 CE FCC DC OUTPUT  
+ = RED  
- = BLUE


UL LISTED E325626  
0-10V DIMMING  
DIM+ = PURPLE  
DIM- = GRAY

REHS Made in China REV: A1.3



**75 Watt - LP75W Series**  
CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

**UL Class P Constant Current Versions**



**IP66**



Part Number <sup>(2)</sup>	US Class 2	CN Class 2	UL Types	Output Voltage Range	Output Constant Current	Current Accuracy	Output Power Maximum	Typical Efficiency <sup>(1)</sup>
LP75W-214-C0350-P	NO	NO	HL	72 - 214 VDC	350 mA	± 3%	75W	91%
LP75W-166-C0450-P	NO	NO	HL	56 - 166 VDC	450 mA	± 3%	75W	91%
LP75W-108-C0700-P	NO	NO	HL	36 - 108 VDC	700 mA	± 3%	75W	90%
LP75W-72-C1050-P	NO	NO	HL	24 - 72 VDC	1050 mA	± 3%	75W	90%
LP75W-54-C1400-P	YES	YES	HL	18 - 54 VDC	1400 mA	± 3%	75W	88%
LP75W-48-C1560-P	YES	YES	HL	16 - 48 VDC	1560 mA	± 3%	75W	88%
LP75W-42-C1790-P	YES	YES	HL	14 - 42 VDC	1790 mA	± 3%	75W	86%
LP75W-36-C2100-P	YES	YES	HL	12 - 36 VDC	2100 mA	± 3%	75W	86%
LP75W-27-C2800-P	YES	YES	HL	9 - 27 VDC	2800 mA	± 3%	75W	85%
LP75W-24-C3130-P <sup>(5)</sup>	YES	YES	HL	8 - 24 VDC	3130 mA	± 3%	75W	85%
LP75W-20-C3750-P	YES	YES	HL	7 - 20 VDC	3750 mA	± 3%	75W	84%
LP75W-15-C5000-P	YES	YES	HL	5 - 15 VDC	5000 mA	± 3%	75W	84%
LP75W-12-C6250 <sup>(5)</sup>	NO	NO	HL	4 - 12 VDC	6250 mA	± 3%	75W	84%

**UL Class P Constant Voltage Versions**

Part Number	US Class 2	CN Class 2	UL Types	Output Constant Voltage	Output Current Range	Voltage Accuracy	Output Power Maximum	Typical Efficiency <sup>(1)</sup>
LP75W-214-P	NO	NO	HL	214 VDC	88 - 350 mA	± 5%	75W	91%
LP75W-166-P	NO	NO	HL	166 VDC	113 - 450 mA	± 5%	75W	91%
LP75W-108-P	NO	NO	HL	108 VDC	175 - 700 mA	± 5%	75W	90%
LP75W-72-P	NO	NO	HL	72 VDC	263 - 1050 mA	± 5%	75W	90%
LP75W-54-P	YES	YES	HL	54 VDC	350 - 1400 mA	± 5%	75W	88%
LP75W-48-P	YES	YES	HL	48 VDC	390 - 1560 mA	± 5%	75W	88%
LP75W-42-P	YES	YES	HL	42 VDC	448 - 1790 mA	± 5%	75W	86%
LP75W-36-P	YES	YES	HL	36 VDC	525 - 2100 mA	± 5%	75W	86%
LP75W-27-P	YES	YES	HL	27 VDC	700 - 2800 mA	± 5%	75W	85%
LP75W-24-P <sup>(5)</sup>	YES	YES	HL	24 VDC	783 - 3130 mA	± 5%	75W	85%
LP75W-20-P	YES	YES	HL	20 VDC	938 - 3750 mA	± 5%	75W	84%
LP75W-15-P	YES	YES	HL	15 VDC	1250 - 5000 mA	± 5%	75W	84%
LP75W-12-P <sup>(5)</sup>	NO	NO	HL	12 VDC	1563 - 6250 mA	± 5%	75W	84%



**Notes**

1. Typical efficiency measured at 230VAC input, full load
2. For dimmable versions add appropriate designator to the end of the part number: For Example: LP75W-15-C5000-PRD is 0-10V or resistance dimmable version, LP75W-15-C5000-PPD is PWM dimmable version.  
-PRD 0-10V & Resistance dimmable version comes with an extra two wires +Purple/-Grey on the output side.  
-PPD PWM Dimmable version comes with an extra two wires +Purple/-Grey on the output side.
3. -PRD 0-10V Dimming is compatible with most quality 0-10V wall dimmers and direct 0-10V analog signal. See page 4 for details.
4. -PPD PWM version is PWM Dimmable via a positive 10% to 100% Duty Cycle, 500Hz to 1.5kHz, 0-10V Pulse. See page 5 for details.
5. SAM Recognized under E325626.

## 75 Watt - LP75W Series

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

DIMMING  
LP75W Series  
**75W**



IP66



### Constant Current Versions

Part Number <sup>(2)</sup>	US Class 2	CN Class 2	UL Types	Output Voltage Range	Output Constant Current	Current Accuracy	Output Power Maximum	Typical Efficiency <sup>(1)</sup>
LP75W-214-C0350	NO	NO	TL & HL	72 - 214 VDC	350 mA	± 3%	75W	91%
LP75W-166-C0450	NO	NO	TL & HL	56 - 166 VDC	450 mA	± 3%	75W	91%
LP75W-108-C0700	NO	NO	TL & HL	36 - 108 VDC	700 mA	± 3%	75W	90%
LP75W-72-C1050	NO	NO	TL & HL	24 - 72 VDC	1050 mA	± 3%	75W	90%
LP75W-54-C1400	YES	YES	TL & HL	18 - 54 VDC	1400 mA	± 3%	75W	88%
LP75W-48-C1560	YES	YES	TL & HL	16 - 48 VDC	1560 mA	± 3%	75W	88%
LP75W-42-C1790	YES	YES	TL & HL	14 - 42 VDC	1790 mA	± 3%	75W	86%
LP75W-36-C2100	YES	YES	TL & HL	12 - 36 VDC	2100 mA	± 3%	75W	86%
LP75W-27-C2800	YES	YES	TL & HL	9 - 27 VDC	2800 mA	± 3%	75W	85%
LP75W-24-C3130 <sup>(5)</sup>	YES	YES	TL & HL	8 - 24 VDC	3130 mA	± 3%	75W	85%
LP75W-20-C3750	YES	YES	TL & HL	7 - 20 VDC	3750 mA	± 3%	75W	84%
LP75W-15-C5000	YES	YES	TL & HL	5 - 15 VDC	5000 mA	± 3%	75W	84%
LP75W-12-C6250 <sup>(5)</sup>	NO	NO	TL & HL	4 - 12 VDC	6250 mA	± 3%	75W	84%

### Constant Voltage Versions

Part Number	US Class 2	CN Class 2	UL Types	Output Constant Voltage	Output Current Range	Voltage Accuracy	Output Power Maximum	Typical Efficiency <sup>(1)</sup>
LP75W-214	NO	NO	TL & HL	214 VDC	88 - 350 mA	± 5%	75W	91%
LP75W-166	NO	NO	TL & HL	166 VDC	113 - 450 mA	± 5%	75W	91%
LP75W-108	NO	NO	TL & HL	108 VDC	175 - 700 mA	± 5%	75W	90%
LP75W-72	NO	NO	TL & HL	72 VDC	263 - 1050 mA	± 5%	75W	90%
LP75W-54	YES	YES	TL & HL	54 VDC	350 - 1400 mA	± 5%	75W	88%
LP75W-48	YES	YES	TL & HL	48 VDC	390 - 1560 mA	± 5%	75W	88%
LP75W-42	YES	YES	TL & HL	42 VDC	448 - 1790 mA	± 5%	75W	86%
LP75W-36	YES	YES	TL & HL	36 VDC	525 - 2100 mA	± 5%	75W	86%
LP75W-27	YES	YES	TL & HL	27 VDC	700 - 2800 mA	± 5%	75W	85%
LP75W-24 <sup>(5)</sup>	YES	YES	TL & HL	24 VDC	783 - 3130 mA	± 5%	75W	85%
LP75W-20	YES	YES	TL & HL	20 VDC	938 - 3750 mA	± 5%	75W	84%
LP75W-15	YES	YES	TL & HL	15 VDC	1250 - 5000 mA	± 5%	75W	84%
LP75W-12 <sup>(5)</sup>	NO	NO	TL & HL	12 VDC	1563 - 6250 mA	± 5%	75W	84%

### Notes

1. Typical efficiency measured at 230VAC input, full load
2. For dimmable versions add appropriate designator to the end of the part number: For Example: LP75W-15-C5000-RD is 0-10V or resistance dimmable version, LP75W-15-C5000-PD is PWM dimmable version.  
-RD 0-10V & Resistance dimmable version comes with an extra two wires +Purple/-Grey on the output side.  
-PD PWM Dimmable version comes with an extra two wires +Purple/-Grey on the output side.
3. -RD 0-10V Dimming is compatible with most quality 0-10V wall dimmers and direct 0-10V analog signal. See page 4 for details.
4. -PD PWM version is PWM Dimmable via a positive 10% to 100% Duty Cycle, 500Hz to 1.5kHz, 0-10V Pulse. See page 5 for details.
5. SAM Recognized under E325626.

# 75 Watt - LP75W Series

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING


### -RD 2-Wire 0-10V CCR Dimming Scheme

Parameters	Minimum	Typical	Maximum
Source Current out of 0-10V Purple Wire	0mA	—	2mA
Absolute Voltage Range on 0-10V (+) Purple Wire	-2.0V	—	+15V
Sink Current into 0-10V Purple Wire	0mA	—	1.2mA


### Notes

1. -RD 0-10V dimmable version comes with an extra two wires +Purple/-Grey on the output side.
2. -RD version is compatible with most 0-10V Wall Slide dimmers and direct 0-10V analog signal.  
Recommended wall slide dimmer is Leviton IP710 or equivalent
3. -RD 0-10V dimmable version is not intended to dim below about 5% @ 0V or 10% @ 1.0V
4. -RD 0-10V dimmable version output will be 100% with Purple/Grey open and minimum with Purple/Grey Shorted.


### -RD 2-Wire Resistance Dimming Scheme



### -RD 2-Wire 0-10V Analog Dimming Scheme



**% Output Current vs. 0-10VDC Dimming Input**



## 75 Watt - LP75W Series

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

**75W**  
 LP75W Series  
 DIMMING


### -PD 2-Wire CCR PWM Positive Dimming Scheme

Parameters	Minimum	Typical	Maximum
Absolute Maximum Voltage Range on PWM Input (Purple Wire)	-2.0V	10V	+15V
Input LOW Level Voltage Range (Purple Wire)	-2.0V	0V	+5.5V
Input HIGH Level Voltage Range (Purple Wire)	+9.0V	10V	+15V
Current into PWM Input (Purple Wire)	0mA	—	1.2mA
Source Current out of PWM Input (Purple Wire)	0mA	—	2mA
PWM Input Signal Frequency	500Hz	—	1500Hz
PWM Input Signal Positive Duty Cycle	0%	10-90%	100%


### Notes

1. -PD PWM Dimmable version comes with an extra 2 wires +Purple/-Grey on the output side.
2. -PD PWM Dimmable version is not intended to dim below about 5% @ 0% Duty Cycle or 10% @ 10% Duty Cycle
3. -PD PWM dimmable version output will be 100% with Purple/Grey open and minimum with Purple/Grey Shorted.

### -PD 2-Wire PWM Positive Dimming Scheme



**% Output Current vs. 1.0 kHz, Positive Duty Cycle Dimming Input**



**75 Watt - LP75W Series**  
CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

**Input Specifications**

Parameter	Min.	Typ.	Max.	Notes/Conditions
Input Voltage	90 Vac	—	305 Vac	120, 230, 240, 277 Vac Nominal Values
Input Frequency	47 Hz	—	63 Hz	50/60Hz Nominal
Input AC Current	—	—	0.71 A	Measured at 120Vac/60Hz Input, Output Full load.
	—	—	0.40 A	Measured at 230Vac/60Hz Input, Output Full load.
Inrush Current (Peak)	—	—	77A	Measured at 277Vac/60Hz Input, Output Full Load, Ta 25°C, Cold Start 50% I <sub>peak</sub> duration ≈250 μsec (1/2*I <sub>p</sub> <sup>2</sup> *t)
Inrush Current (I <sup>2</sup> t)	—	—	0.74 A <sup>2</sup> s	
Leakage Current	—	—	0.68mA	Measured at 120Vac/60Hz Input, Output Full load.
	—	—	0.75mA	Measured at 277Vac/60Hz Input, Output Full load.
THD	—	—	20%	Measured at 120, 230, 277Vac Input, Output ≥60% Load
Power Factor (PF)	0.90	—	—	Measured at 120, 230, 277Vac Input, Output ≥75% Load

**Output Specifications**

Parameter	Min.	Typ.	Max.	Notes/Conditions
DC Output Voltage	Per Table	—	Per Table	Per Tables on Page 2 & 3
DC Output Constant Current	-3%	Per Table	+3%	Per Tables on Page 2 & 3
Output Power	—	—	Per Table	Per Tables on Page 2 & 3
Ripple & Noise (V <sub>pk-pk</sub> )	—	—	5% V <sub>o</sub>	20 MHz BW, Full load output in parallel with 0.1 μF ceramic & 10 μF Electrolytic.
Ripple (I <sub>pk-pk</sub> )	—	—	5% I <sub>o</sub>	20 MHz BW, Full load output in parallel with 0.1 μF ceramic & 10 μF Electrolytic. 120 Hz component (Flicker Free)
Start-up Time	—	200 mS	500 mS	Measured at 120Vac/60Hz Input, Output Full load.
Hold-up Time	—	40 mS	—	Typical @ 277Vac Input, Output Full load.

**Environmental Specifications**

Parameter	Min.	Typ.	Max.	Notes/Conditions
Case Temperature (T <sub>c</sub> )	-30 °C	—	+90 °C	Measured at location specified on case.
Operating Temperature (T <sub>a</sub> )	-30 °C	—	+60 °C	This is a reference range. T <sub>c</sub> controls temperature range.
Storage Temperature (T <sub>s</sub> )	-40 °C	—	+85 °C	Non operating temperature range.
Operating Humidity	—	—	95% RH	Relative Humidity, non-condensing.
Vibration	5 Hz	—	55 Hz	2G, 10 minutes/1 cycle, period 30 minutes, each along X, Y, Z axis.
MTBF	474,000 Hours	—	—	MIL-HDBK-217F Notice 2, T <sub>a</sub> = 25C, Output Full Load.

**Protection Specifications**

Parameter	Min.	Typ.	Max.	Notes/Conditions
Output Short Circuit (SCP)	—	—	—	No Damage, Auto recovery after short is removed.
Output Over Current (OCP)	—	—	+8% I <sub>o</sub>	Constant Current Limiting circuit.
Output Over Voltage (OVP)	—	—	120% V <sub>o</sub>	No Damage, Auto recovery after fault is removed.



## 75 Watt - LP75W Series

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

DIMMING  
LP75W Series  
**75W**

### Safety Compliance


Safety	Notes/Standards
UL Class P UL/CUL Listed	UL8750 & CAN/CSA C22.2 No. 250.13, UL Class P, UL Type HL
UL Type TL UL/CUL Recognized	UL8750, UL1310 for UL Class 2 & CAN/CSA C22.2 No. 250.13, UL Type HL & UL Type TL UL Class 2 86/63°C, UL Non-Class 2 90/81°C
CE	EN61347-1, EN61347-2-13
Withstand Voltage	Input to Output: 3750 Vac. Parts use a GDT. Hipot cannot be done with Case or GND connected.
Isolation Resistance	Input to Output: >100 MΩ, 500VDC @ 25 °C, 70 % RH
Dimming Circuit	Dim+ Purple/Dim- Grey are considered part of the secondary circuit.

### EMC Compliance

Standard	Notes/Conditions
FCC, 47CFR Part 15	Class B
EN 55015	Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment.
EN 61000-3-2	Part 3-2: Limits for harmonic current emissions Class C, $\geq 80\%$ Rated Power
EN 61000-3-3	Part 3-3: Limitation of voltage changes, voltage fluctuations and flicker.
EN 61000-4-5	Part 4-5: Surge Immunity test, 2kV L-N, 4kV L-FG & N-FG
Energy Star	Energy Star transient protection: Ballast or driver shall comply with ANSI/IEEE C62.41.1-2002 and ANSI/IEEE C62.41.2-2002, Category A operation. The line transient shall consist of seven strikes of a 100 kHz ring wave, 2.5 kV level, for both common mode and differential mode.

### Power Factor Curves (Typical)


PF vs. Output Power



**75 Watt - LP75W Series**  
CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING


**THD Curves (Typical)**

**THD vs. Output Power**



**Efficiency Curve (Typical)**

**Efficiency vs. Output Power**






## 75 Watt - LP75W Series

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

**75W**  
 LP75W Series  
 DIMMING


### Life vs. Ambient Temperature

LP75W Estimated Life Full Load @ 120Vac



### Life vs. Case (Tc) Temperature

LP75W Estimated Life Full Load @ 120Vac



**75W**

**LP75W Series**

DIMMING



**LED Optimized Drivers**

## **75 Watt - LP75W Series**

CONSTANT VOLTAGE OR CONSTANT CURRENT LED DRIVER WITH DIMMING

