THIS DRAWING CONTAINS INFORMATION THAT IS PROPRIETARY TO J.S.T. AND SHALL NOT BE USED OR SHOWN WITHOUT WRITTEN PERMISSION.

ITEM	CONNECTOR PART NO.	DESCRIPTION
1	SXAM-01T-P0.6	XA W-W CONNECTOR CONTACT
2	UL1007, 22 AWG	BLACK

Applicable Housings

XA Series			XAD Series	
NO. OF CIRCUITS	HOUSING PART NO. WITH PANEL LOCKS	HOUSING PART NO. WITHOUT PANEL LOCKS	NO. OF CIRCUITS	HOUSING PART NO.
2	XARR-02V	XARR-02VF	8	XADR-08V
3	XARR-03V	XARR-03VF	10	XADR-10V
4	XARR-04V	XARR-04VF	12	XADR-12V
5	XARR-05V	XARR-05VF	14	XADR-14V
6	XARR-06V	XARR-06VF	16	XADR-16V
7	XARR-07V	-	18	XADR-18V
8	XARR-08V	XARR-08VF	20	XADR-20V
9	XARR-09V	XARR-09VF	22	XADR-22V
10	XARR-10V	XARR-10VF	24	XADR-24V
11	XARR-11V	-	26	XADR-26V
12	XARR-12V	XARR-12VF	28	XADR-28V
13	XARR-13V	-	30	XADR-30V
14	XARR-14V	-	32	XADR-32V
15	XARR-15V	-	34	XADR-34V
			36	XADR-36V
			40	XADR-40V



Electrical Specifications
Current: 3.0A AC/DC
Voltage: 250V AC/DC

REV.	DESCRIPTION	DATE	BY
2	Add electrical specifications	7/2/2018	SP
1	Added housing part numbers for the XAD series	12/21/2017	SP

SCALE: 1: 1

DIMENSIONS: All dimensions are in MM with a tolerance of +/- 3.0 unless otherwise specified.

DESCRIPTION: 2.5 mm Pitch XA & XAD W-W Series Standard Leads - 2" Inside Length
DOUBLE-END LEADS, M-M

DRAWN BY: STEVEN PILKINGTON

ASSEMBLY PART NO.: ASXAMSXAM22K51

CHECKED BY: JUSTIN BAKER

DRAWING NO.: GAM-073

DATE: 3/9/2016